# Transformer for BCM94706NR

CEEH96

**Electrical characteristics**

| Part No. | Item | Inductance (3-4) | | Leakage inductance | Turns ratio 100kHz, & 0.1Vac. | | | |
|---|---|---|---|---|---|---|---|---|
| C8100 | Specifications | Max. 3.38μH | Min. 2.7μH | Max. 0.16μH | 1.03 (±7%) | 1.04 (±7%) | 2.77 (±7%) | 2.75 (±7%) |
| | Testing conditions | 100kHz 0.1Vac @20℃ | 6.0Adc for 0.25 sec. 100kHz 0.1Vac @25℃ | 100kHz, 0.1Vrms (3-4) STRAP 1,2,7,8 | (1-8):(2-7) | (1-8):(8-2) | (1-8):(3-5) | (1-8):(5-4) |

| Part No. | Item | D.C.R. 20℃ | | | | | Breakdown voltage for 2 seconds | |
|---|---|---|---|---|---|---|---|---|
| C8100 | Specifications | Max. 0.44Ω | Max. 0.48Ω | Max. 0.52Ω | Max. 0.06Ω | Max. 0.07Ω | Min.500Vrms | Min.500Vrms |
| | Testing conditions | (1-8) | (8-2) | (2-7) | (3-5) | (5-4) | 1,2,7,8 to 3,4,5,6 & core | 1,2,7,8 & core to 3,4,5,6 |

For sales office information, please click here to visit our website.

Remarks： Sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text sample text.

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Sumida:
C8100