

				TEST				IFAL	AGE
	V <sub>Z</sub> @ I <sub>ZT</sub>		CURRENT	REGULAR IMPEDANCE		TEST CURRENT	LEAKAGE CURRENT		
PART NUMBER			I <sub>ZT</sub>	Z <sub>ZT</sub> @ I <sub>ZT</sub>	$Z_{ZK} @ I_{ZK}$	I <sub>ZK</sub>	V <sub>z</sub> @ I <sub>zt</sub>		
							V m		
	Min.	Nom.	Max.		Max.	Max.		Max.	
BZX79B2V4	2.35	2.40	2.45	5	100	600	1.0	100	1.0
BZX79B2V7	2.65	2.70	2.75	5	100	600	1.0	75	1.0
BZX79B3V0	2.94	3.00	3.06	5	95	600	1.0	50	1.0
BZX79B3V3	3.23	3.30	3.37	5	95	600	1.0	25	1.0
BZX79B3V6	3.53	3.60	3.67	5	90	600	1.0	15	1.0
BZX79B3V9	3.82	3.90	3.98	5	90	600	1.0	10	1.0
BZX79B4V3	4.21	4.30	4.39	5	90	600	1.0	5	1.0
BZX79B4V7	4.61	4.70	4.79	5	80	500	1.0	3.0	2.0
BZX79B5V1	5.00	5.10	5.2	5	60	480	1.0	2.0	2.0
BZX79B5V6	5.49	5.60	5.71	5	40	400	1.0	1.0	2.0
BZX79B6V2	6.08	6.20	6.32	5	10	150	1.0	3.0	4.0
BZX79B6V8	6.66	6.80	6.94	5	15	80	1.0	2.0	4.0
BZX79B7V5	7.35	7.50	7.65	5	15	80	1.0	1.0	5.0
BZX79B8V2	8.04	8.20	8.36	5	15	80	1.0	0.7	5.0
BZX79B9V1	8.92	9.10	9.28	5	15	100	1.0	0.5	6.0
BZX79B10	9.80	10.00	10.2	5	20	150	1.0	0.2	7.0
BZX79B11	10.78	11.00	11.22	5	20	150	1.0	0.1	8.0
BZX79B12	11.76	12.00	12.24	5	25	150	1.0	0.1	8.0
BZX79B13	12.74	13.00	13.26	5	30	170	1.0	0.1	8.0
BZX79B15	14.70	15.00	15.30	5	30	200	1.0	0.05	10.5
BZX79B16	15.68	16.00	16.32	5	40	200	1.0	0.05	11.2
BZX79B18	17.64	18.00	18.36	5	45	225	1.0	0.05	12.6
BZX79B20	19.60	20.00	20.40	5	55	225	1.0	0.05	14.0
BZX79B22	21.56	22.00	22.44	5	55	250	1.0	0.05	15.4
BZX79B24	23.52	24.00	24.48	5	70	250	1.0	0.05	16.8
BZX79B27	26.46	27.00	27.54	2	80	300	0.5	0.05	18.9
BZX79B30	29.40	30.00	30.60	2	80	300	0.5	0.05	21.0
BZX79B33	32.34	33.00	33.66	2	80	325	0.5	0.05	23.1
BZX79B36	35.28	36.00	36.72	2	90	350	0.5	0.05	25.2
BZX79B39	38.22	39.00	39.78	2	130	350	0.5	0.05	27.3
BZX79B43	42.14	43.00	43.86	2	150	375	0.5	0.05	30.1
BZX79B47	46.06	47.00	47.94	2	170	375	0.5	0.05	32.9
BZX79B51	49.98	51.00	52.02	2	180	400	0.5	0.05	35.7
BZX79B56	54.88	56.00	57.12	2	200	425	0.5	0.05	39.2
BZX79B62	60.76	62.00	63.24	2.5	215	430	0.5	0.05	43.4
BZX79B68	66.64	68.00	69.36	2.5	240	447	0.5	0.05	47.6
BZX79B75	73.50	75.00	76.50	2.5	255	470	0.5	0.05	52.5



Taiwan Semiconductor

#### Notes:

- 1. Tolerance and voltage designation : the type numbers listed have Zener voltage as shown
- 2. Specials available include, nominal zener voltages between the voltages shown and tighter voltage, for detailed
- 3. Zener voltage (VZ) measurement, the zener voltage is measured under pulse condicitons such that TJ is no more than 2oC above TA
- 4. Zener impedance (ZZ) derivaton, zener impedance is derived from the 60-cycle ac voltage, which results when an ac current having an RMS value equal to 10% of the dc zener current (IZT) is superimposed to IZT

ORDERING INFORMATION						
PART NO.	PACKING CODE	PACKING CODE SUFFIX	PACKAGE	PACKING		
BZX79BXXX (Note 1&2)	R0	6	DO-35	10K / 14" Reel		
	A0	G		5K / Box (Ammo)		

#### Notes:

- 1. "xxx" defines voltage from 2.4V (BZX79B2V4) to 75V (BZX79B75)
- 2. Whole series with green compound


EXAMPLE						
EXAMPLE P/N PART NO.		PACKING CODE	PACKING CODE SUFFIX	DESCRIPTION		
BZX79B75 R0G	BZX79B75	R0	G	Green compound		

3




Taiwan Semiconductor

### **PACKAGE OUTLINE DIMENSION**



DIM.	Unit(	mm)	Unit(inch)		
	Min	Max	Min	Max	
А	0.34	0.60	0.013	0.024	
В	2.90	5.08	0.114	0.200	
С	25.40	38.10	1.000	1.500	
D	1.30	2.28	0.051	0.090	

## **MARKING DIAGRAM**





Taiwan Semiconductor

## **Notice**

Specifications of the products displayed herein are subject to change without notice. TSC or anyone on its behalf, assumes no responsibility or liability for any errors or inaccuracies.

Information contained herein is intended to provide a product description only. No license, express or implied, to any intellectual property rights is granted by this document. Except as provided in TSC's terms and conditions of sale for such products, TSC assumes no liability whatsoever, and disclaims any express or implied warranty, relating to sale and/or use of TSC products including liability or warranties relating to fitness for a particular purpose, merchantability, or infringement of any patent, copyright, or other intellectual property right.

The products shown herein are not designed for use in medical, life-saving, or life-sustaining applications. Customers using or selling these products for use in such applications do so at their own risk and agree to fully indemnify TSC for any damages resulting from such improper use or sale.

# **Mouser Electronics**

**Authorized Distributor** 

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

### Taiwan Semiconductor:

BZX79B10 BZX79B11 BZX79B12 BZX79B13 BZX79B15 BZX79B16 BZX79B18 BZX79B20 BZX79B22
BZX79B24 BZX79B27 BZX79B2V4 BZX79B2V7 BZX79B30 BZX79B30 BZX79B3V0 BZX79B3V3 BZX79B3V6
BZX79B3V9 BZX79B47 BZX79B4V3 BZX79B4V7 BZX79B5V1 BZX79B5V6 BZX79B62 BZX79B68 BZX79B6V2
BZX79B75 BZX79B7V5 BZX79B8V2 BZX79B8V1 BZX79B3V3 ROG BZX79B5V1 ROG BZX79B39 ROG
BZX79B2V4 ROG BZX79B9V1 ROG BZX79B3V ROG BZX79B3V3 ROG BZX79B3V9 ROG BZX79B75 ROG
BZX79B18 ROG BZX79B24 ROG BZX79B27 ROG BZX79B68 ROG BZX79B3V9 ROG BZX79B8V2 ROG
BZX79B2V7 ROG BZX79B22 ROG BZX79B27 ROG BZX79B4V7 ROG BZX79B3V9 ROG BZX79B3V0 ROG BZX79B20 ROG BZX79B5V6 ROG BZX79B11 ROG BZX79B15 ROG BZX79B5V6 ROG BZX79B18 ROG BZX79B13 ROG BZX79B10 ROG BZX79B12 ROG BZX79B5V6 ROG BZX79B16 ROG
BZX79B4V3 ROG BZX79B13 ROG BZX79B3V6 ROG BZX79B3V0 AOG BZX79B5V6 ROG BZX79B56 AOG
BZX79B2V7 AOG BZX79B24 AOG BZX79B3V6 ROG BZX79B3V0 AOG BZX79B33 AOG BZX79B30 AOG BZX79B3V6 AOG BZX79B5V6 A